

 <p><b>UŽIVATELSKÝ NÁVOD</b></p> <p><b>07812L</b></p> <p>Výrobce a dovozce: IMMAX, Teslova 1179/2, 702 00 Ostrava, EU www.immax.cz   www.immax.eu Vyrobeno v P.R.C.</p>  <p><b>APLIKACE IMMAX NEO PRO</b></p>	<p><b>TECHNICKÁ SPECIFIKACE:</b></p> <p>Barva: bílá Podsvícení: RGB Protokol: Wi-Fi IEEE 802.11b/g/n Frekvence: 2400MHz-2483.5MHz Maximální RF výstupní výkon: WiFi: 20dBm Bezdrátový dosah: 30 m přímá viditelnost, 5 m v zastaveném prostoru Jmenovité napětí: AC 230V ± 10%, 50/60 Hz Maximální zatížení: 3500W, 16A Ochrana proti přepětí: 265V Ochrana proti podpětí: 90V Pracovní teplota: 0 °C ~ 40 °C (32 °F ~ 104 °F) Pracovní vlhkost: 10% ~ 90% Stupeň krytí: IP20 Funkce v aplikaci: ZAP / VYP, Časovač, Odpočet, Měření spotřeby Velikost: 4,4 cm x 8,2 cm Váha: 66g Obsah balení: Vnitřní zásuvka, uživatelský manuál</p> <p><b>STÁHNUTÍ APLIKACE IMMAX NEO PRO A REGISTRACE</b></p> <p>Naskenujte kód QR a stáhněte si aplikaci Immax NEO PRO.</p> <p>Nebo v App Store nebo Google Play vyhledejte a nainstalujte aplikaci Immax NEO PRO a</p> <ul style="list-style-type: none"> <li>- Spusťte aplikaci Immax NEO PRO a klepněte na „Registrovat“ a založte si vlastní účet.</li> <li>- Pokud máte registraci hotovou, přihlaste se pod svůj účet.</li> </ul>	<p><b>LED PODSVÍCENÍ</b></p> <p>Modrá barva: zásuvka je vypnutá. Bílá barva: zásuvka je zapnutá. Zelená barva: zásuvka je zapnutá a její zatížení je pod 80%. Červená barva: zatížení zásuvky přesahuje 80 % plnění zatížení. Indikace vysoké spotřeby elektrické energie. Blikající modrá barva: zásuvka je v párovacím módu. Blikající červená barva: chyba připojení k síti.</p> <p><b>PÁROVÁNÍ PRODUKTU DO APLIKACE</b></p> <p>Příprava: Zapněte zařízení a otevřete aplikaci Immax NEO PRO.</p> <p>Ujistěte se, že jste připojeni na stejnou WiFi síť, na kterou bude připojen daný produkt.</p> <p>Možnost přidání pomocí Bluetooth Proveďte reset zařízení – dlouze stiskněte tlačítko na zařízení na více než 5 vteřin. LED kontrolka na zařízení začne rychle blikat. Pokud nemáte zapnutý Bluetooth na svém mobilním zařízení, tak budete k tomu vyzváni. Po zapnutí Bluetooth mobilní zařízení automaticky najde daný produkt. V aplikaci se zobrazí okno s informací o nalezení nového zařízení. Klikněte na tlačítko „Pokračovat“ a potom na tlačítko „+“. Zadejte přístupové údaje do WiFi sítě a potvrďte. Potom se daný produkt spáruje a přidá aplikace Immax NEO PRO.</p> <p><b>MOŽNOST PŘIDÁNÍ BEZ POMOCI BLUETOOTH</b></p> <p>Proveďte reset zařízení – dlouze stiskněte tlačítko na zařízení na více než 5 vteřin. LED kontrolka na zařízení začne rychle blikat. V aplikaci Immax NEO PRO klikněte na záložku Místnost a potom na tlačítko „+“ Po přidání zařízení. V záložce Immax NEO vyberte produkt. Zadejte přístupové údaje do WiFi sítě a potvrďte. Potom se</p>	<p>daný produkt spáruje a přidá do aplikace Immax NEO PRO.</p> <p><b>ZKRÁCENÁ VERZE PROHLÁŠENÍ O SHODĚ</b></p> <p>Tímto výrobce IMMAX prohlašuje, že typ rádiového zařízení 07812L je v souladu se směrnicí 2014/53/EU. Úplné znění EU prohlášení o shodě je k dispozici na těchto internetových stránkách www.immax.cz, www.immax.eu</p> <p>Bezpečnostní informace k tomuto výrobku si můžete stáhnout ze stránek www.immax.cz</p> <p>Pokud máte dotaz nebo potřebujete poradit, kontaktujte nás na adrese podpora@immaxneo.cz.</p> <p><b>POZNÁMKY</b></p> <p>Symbol  vyjadřuje, výrobek nesmí být likvidován s komunálním odpadem. Pro správnou likvidaci výrobku jej odevzdejte na určených sběrných místech. Při likvidaci vyjměte za zařízení baterie a žárovky – pokud to lze. Starý spotřebič odevzdejte ve sběrnách k tomu určených, nepatří do komunálního odpadu. Odpadní elektrická a elektronická zařízení ze soukromých domácností lze zdarma odevzdat na veřejných sběrných místech Jako koncový uživatel odevzdáváte za výmaz osobních údajů ze starého spotřebiče ASEKOL: AK-016010, WEEE-Reg.-Nr. DE 88927148</p>   
 <p><b>UŽIVATELSKÝ NÁVOD</b></p> <p><b>07812L</b></p> <p>Manufacturer and importer: IMMAX, Teslova 1179/2, 702 00 Ostrava, EU www.immax.cz   www.immax.eu Made in P.R.C.</p>  <p><b>IMMAX NEO PRO APPLICATION</b></p>	<p><b>TECHNICAL SPECIFICATIONS:</b></p> <p>Color: white Backlight: RGB Protocol: Wi-Fi IEEE 802.11b/g/n Frequency: 2400MHz-2483.5MHz Maximum RF output power: WiFi: 20dBm Wireless range: 30 m line of sight, 5 m in built-up areas Nominal voltage: AC 230V ± 10%, 50/60 Hz Maximum load: 3500W, 16A Overvoltage protection: 265V Undervoltage protection: 90V Operating temperature: 0 °C ~ 40 °C (32 °F ~ 104 °F) Operating humidity: 10% ~ 90% Protection rating: IP20 Functions in the app: ON/OFF, Timer, Countdown, Consumption measurement Size: 4.4 cm x 8.2 cm Weight: 66g Package contents: Internal socket, user manual</p> <p><b>DOWNLOAD IMMAX NEO PRO AND REGISTER</b></p> <p>Scan the QR code and download the Immax NEO PRO app.</p> <p>Or search for and install the Immax NEO PRO app in the App Store or Google Play.</p> <ul style="list-style-type: none"> <li>- Launch the Immax NEO PRO app and tap "Register" to create your own account.</li> <li>- Once you have completed registration, log in with your account.</li> </ul>	<p><b>LED BACKLIGHT</b></p> <p>Blue: the socket is switched off. White: the socket is switched on. Green: the socket is switched on and its load is below 80%. Red: the socket load exceeds 80% of full load. Indicates high power consumption. Flashing blue: the socket is in pairing mode. Flashing red: network connection error.</p> <p><b>PAIRING THE PRODUCT TO THE APPLICATION</b></p> <p>Preparation: switch on the device and open the Immax NEO PRO app. Make sure you are connected to the same WiFi network that the product.</p> <p><b>BLUETOOTH ADD-ON OPTION</b></p> <p>Reset the device - long press the button on the device for more than 5 seconds. The LED light on the device will flash rapidly. If you do not have Bluetooth enabled on your mobile device, you will be prompted to do so. Once Bluetooth is turned on, the mobile device will automatically find the product. A window will appear in the app informing you that a new device has been found. Click the "Continue" button and then the "+" button. Enter the access WiFi network and confirm. The product will then be paired and the Immax NEO PRO app will be added.</p> <p><b>OPTION TO ADD WITHOUT USING BLUETOOTH</b></p> <p>Perform a device reset - long press the button on the device for more than 5 seconds. The LED light on the device will flash rapidly. In the Immax NEO PRO app, click on the Room tab and then on the "+" button. button to add the device. In the Immax NEO tab, select</p>	<p>the product. Enter the access WiFi network and confirm. The product will then be paired and added to the app Immax NEO PRO.</p> <p><b>SHORT VERSION OF THE DECLARATION OF CONFORMITY</b></p> <p>The manufacturer IMMAX hereby declares that type 07812L radio equipment complies with Directive 2014/53/EU. The full text of the EU Declaration of Conformity is available on the following websites: www.immax.cz, www.immax.eu</p> <p>Safety information for this product can be downloaded from www.immax.eu</p> <p>If you have any questions or need advice, please contact us at podpora@immaxneo.cz.</p> <p><b>NOTES</b></p> <p>The symbol  indicates the product must not be disposed of with municipal waste. To dispose of the product properly, take it to the designated collection points. When disposing of it, remove the batteries and bulbs behind the device - if possible. Dispose of old appliances at designated collection points; they do not belong in municipal waste. Waste electrical and electronic equipment from private households can be handed in free of charge at public collection points As the end user, you are responsible for deleting personal data from the old appliance. ASEKOL: AK-016010, WEEE-Reg.-No. DE 88927148</p>   