

 <p>UŽIVATELSKÝ NÁVOD</p> <p>07813L</p> <p>Výrobce a dovozce: IMMAX, Teslova 1179/2, 702 00 Ostrava, EU www.immax.cz www.immax.eu Vyrobeno v P.R.C.</p>  <p>APLIKACE IMMAX NEO PRO</p>	<p>TECHNICKÁ SPECIFIKACE:</p> <p>Barva: bílá Podsvícení: RGB Protokol: Wi-Fi IEEE 802.11b/g/n Frekvence: 2400MHz-2483.5MHz Maximální RF výstupní výkon: WiFi: 20dBm Bezdrátový dosah: 30 m přímá viditelnost, 5 m v zastaveném prostoru Jmenovité napětí: AC 230V ± 10%, 50/60 Hz Maximální zatížení: 3500W, 16A Ochrana proti přepětí: 265V Ochrana proti podpětí: 90V Pracovní teplota: 0 °C ~ 40 °C (32 °F ~ 104 °F) Pracovní vlhkost: 10% ~ 90% Stupeň krytí: IP20 Funkce v aplikaci: ZAP / VYP, Časovač, Odpočet, Měření spotřeby Velikost: 4,4 cm x 8,2 cm Váha: 66g Obsah balení: Vnitřní zásuvka, uživatelský manuál</p> <p>STÁHNUTÍ APLIKACE IMMAX NEO PRO A REGISTRACE</p> <p>Naskenujte kód QR a stáhněte si aplikaci Immax NEO PRO.</p> <p>Nebo v App Store nebo Google Play vyhledejte a nainstalujte aplikaci Immax NEO PRO.</p> <ul style="list-style-type: none"> - Spusťte aplikaci Immax NEO PRO a klepněte na „Registrovat“ a založte si vlastní účet. - Pokud máte registraci hotovou, přihlaste se pod svůj účet. 	<p>LED PODSVÍCENÍ</p> <p>Modrá barva: zásuvka je vypnutá. Bílá barva: zásuvka je zapnutá. Zelená barva: zásuvka je zapnutá a její zatížení je pod 80%. Červená barva: zatížení zásuvky přesahuje 80 % plného zatížení. Indikace vysoké spotřeby elektrické energie. Blikající modrá barva: zásuvka je v párovacím módu. Blikající červená barva: chyba připojení k síti.</p> <p>PÁROVÁNÍ PRODUKTU DO APLIKACE</p> <p>Příprava: Zapněte zařízení a otevřete aplikaci Immax NEO PRO.</p> <p>Ujistěte se, že jste připojeni na stejnou WiFi síť, na kterou bude připojen daný produkt.</p> <p>Možnost přidání pomocí Bluetooth Proveďte reset zařízení – dlouze stiskněte tlačítko na zařízení na více než 5 vteřin. LED kontrolka na zařízení začne rychle blikat. Pokud nemáte zapnutý Bluetooth na svém mobilním zařízení, tak budete k tomu vyzváni. Po zapnutí Bluetooth mobilní zařízení automaticky najde daný produkt.V aplikaci se zobrazí okno s informací o nalezení nového zařízení.</p> <p>Klikněte na tlačítko „Pokračovat“ a potom na tlačítko „+“.</p> <p>Zadejte přístupové údaje do WiFi sítě a potvrďte. Potom se daný produkt spáruje a přidá aplikace Immax NEO PRO.</p> <p>MOŽNOST PŘIDÁNÍ BEZ POMOCI BLUETOOTH</p> <p>Proveďte reset zařízení – dlouze stiskněte tlačítko na zařízení na více než 5 vteřin. LED kontrolka na zařízení začne rychle blikat. V aplikaci Immax NEO PRO klikněte na záložku Místnost a potom na tlačítko „+“ pro přidání zařízení. V záložce Immax NEO vyberte produkt. Zadejte přístupové údaje do WiFi sítě a potvrďte. Potom se</p>	<p>daný produkt spáruje a přidá do aplikace Immax NEO PRO.</p> <p>ZKRÁCENÁ VERZE PROHLÁŠENÍ O SHODĚ</p> <p>Tímto výrobce IMMAX prohlašuje, že typ rádiového zařízení 07813L je v souladu se směrnicí 2014/53/EU. Úplné znění EU prohlášení o shodě je k dispozici na těchto internetových stránkách www.immax.cz, www.immax.eu</p> <p>Bezpečnostní informace k tomuto výrobku si můžete stáhnout ze stránek www.immax.cz</p> <p>Pokud máte dotaz nebo potřebujete poradit, kontaktujte nás na adrese podpora@immaxneo.cz.</p> <p>POZNÁMKY</p> <p>Symbol  vyjadřuje, výrobek nesmí být likvidován s komunálním odpadem. Pro správnou likvidaci výrobku jej odevzdejte na určených sběrných místech.</p> <p>Při likvidaci vyjměte za zařízení baterie a žárovky – pokud to lze.</p> <p>Starý spotřebič odevzdejte ve sběrnách k tomu určených, nepatří do komunálního odpadu.</p> <p>Odpadní elektrická a elektronická zařízení ze soukromých domácností lze zdarma odevzdat na veřejných sběrných místech</p> <p>Jako koncový uživatel odevzdáte za výmaz osobních údajů ze starého spotřebiče</p> <p>ASEKOL: AK-016010, WEEE-Reg.-Nr. DE 88927148</p>   
 <p>UŽIVATELSKÝ NÁVOD</p> <p>07813L</p> <p>Manufacturer and importer: IMMAX, Teslova 1179/2, 702 00 Ostrava, EU www.immax.cz www.immax.eu Made in P.R.C.</p>  <p>IMMAX NEO PRO APPLICATION</p>	<p>TECHNICAL SPECIFICATIONS:</p> <p>Color: white Backlight: RGB Protocol: Wi-Fi IEEE 802.11b/g/n Frequency: 2400MHz-2483.5MHz Maximum RF output power: WiFi: 20dBm Wireless range: 30 m line of sight, 5 m in built-up areas Nominal voltage: AC 230V ± 10%, 50/60 Hz Maximum load: 3500W, 16A Overvoltage protection: 265V Undervoltage protection: 90V Operating temperature: 0 °C ~ 40 °C (32 °F ~ 104 °F) Operating humidity: 10% ~ 90% Protection rating: IP20 Functions in the app: ON/OFF, Timer, Countdown, Consumption measurement Size: 4.4 cm x 8.2 cm Weight: 66g Package contents: Internal socket, user manual</p> <p>DOWNLOAD IMMAX NEO PRO AND REGISTER</p> <p>Scan the QR code and download the Immax NEO PRO app.</p> <p>Or search for and install the Immax NEO PRO app in the App Store or Google Play.</p> <ul style="list-style-type: none"> - Launch the Immax NEO PRO app and tap "Register" to create your own account. - Once you have completed registration, log in with your account. 	<p>LED BACKLIGHT</p> <p>Blue: the socket is switched off. White: the socket is switched on. Green: the socket is switched on and its load is below 80%. Red: the socket load exceeds 80% of full load. Indicates high power consumption. Flashing blue: the socket is in pairing mode. Flashing red: network connection error.</p> <p>PAIRING THE PRODUCT TO THE APPLICATION</p> <p>Preparation: switch on the device and open the Immax NEO PRO app.</p> <p>Make sure you are connected to the same WiFi network that the product.</p> <p>BLUETOOTH ADD-ON OPTION</p> <p>Reset the device - long press the button on the device for more than 5 seconds. The LED light on the device will flash rapidly.</p> <p>If you do not have Bluetooth enabled on your mobile device, you will be prompted to do so. Once Bluetooth is turned on, the mobile device will automatically find the product.</p> <p>A window will appear in the app informing you that a new device has been found.</p> <p>Click the "Continue" button and then the "+" button.</p> <p>Enter the access WiFi network and confirm. The product will then be paired and the Immax NEO PRO app will be added.</p> <p>OPTION TO ADD WITHOUT USING BLUETOOTH</p> <p>Perform a device reset - long press the button on the device for more than 5 seconds. The LED light on the device will flash rapidly.</p> <p>In the Immax NEO PRO app, click on the Room tab and then on the "+" button.</p> <p>button to add the device. In the Immax NEO tab, select</p>	<p>the product. Enter the access WiFi network and confirm. The product will then be paired and added to the app Immax NEO PRO.</p> <p>SHORT VERSION OF THE DECLARATION OF CONFORMITY</p> <p>The manufacturer IMMAX hereby declares that type 07813L radio equipment complies with Directive 2014/53/EU. The full text of the EU Declaration of Conformity is available on the following websites: www.immax.cz, www.immax.eu</p> <p>Safety information for this product can be downloaded from www.immax.eu</p> <p>If you have any questions or need advice, please contact us at podpora@immaxneo.cz.</p> <p>NOTES</p> <p>The symbol  indicates the product must not be disposed of with municipal waste. To dispose of the product properly, take it to the designated collection points.</p> <p>When disposing of it, remove the batteries and bulbs behind the device - if possible.</p> <p>Dispose of old appliances at designated collection points; they do not belong in municipal waste.</p> <p>Waste electrical and electronic equipment from private households can be handed in free of charge at public collection points</p> <p>As the end user, you are responsible for deleting personal data from the old appliance.</p> <p>ASEKOL: AK-016010, WEEE-Reg.-No. DE 88927148</p>   